

DriveMaster 2010 Pro SATA Tech Specs and System Requirements

ULINK Technology, Inc.

ULINK's DriveMaster 2010 Professional SATA (DM 2010 Pro SATA) Serial consists of three products:

- DM 2010 Pro SATA Single
- DM 2010 Pro SATA Multi
- DM 2010 Pro SATA Network, which includes License Server & Client Station

DriveMaster 2010 Pro SATA Tech Specs

- Conform to ATA/ATAPI-8, MMC and Mt. Fuji 7 specs
- Support standard & user defined ATA/ATAPI commands
- C-like script language
- Microsoft Windows interface

System Requirements

DM 2010 Pro SATA Single/Multi/Network Client Station

- Operating System: Windows 7, Windows Vista , XP or 2003 Operating System
- CPU: Duo Core or above, hyper-threading is recommended
- RAM: 1 GB or above
- Motherboard with SATA Controller based on the Intel ICHx(R) chipset or equivalent (e.g. HP with AMD chipset or VIA system)
- One PCI/PCI-E to ATA or SATA add-on card (e.g. Promise TX2 plus or equivalent) for booting up OS
- 32 MB video card, 64MB and above is recommended.
- System Drive: minimum 100MB free space

DM 2010 Pro SATA Network License Server

- Operating System: Windows XP and above
- System Drive: Minimum 5MB free space
- A network card

Hardware Platform Supported by DriveMaster 2010 Pro SATA

- **Intel** ICH10/9/8/7 (IDE, AHCI, and RAID mode)
- **Marvell**
 - 61XX PCI-E Series (6121, 6141, 6145)
 - 88SX6081 PCI-X SATA II
- **Silicon Image**
 - Sil3124 PCI-X
 - Sil3132 PCI-E
 - Sil3531 PCI-E
- **Generic AHCI Platform**
 - AMD
 - JMicron
 - NVIDIA
 - SIS
 - VIA
- **Generic IDE/PATA**

Recommendations for DM 2010 Pro SATA Single/Multi/Network Client Station

In order to run DriveMaster 2010 Pro SATA to its premium, here are some of hardware recommendations:

- CPU: Intel® Core 2 Duo E6400 or above
- HBA: Integrated with Intel ICH10R/ICH9R Chipset
- RAM: 2GB DDR2/DDR3 or above
- Motherboard: Intel DP45SG (P45 ICH10R) or Intel DP35DP (P35 ICH9R)
- Video Card: ATI Radeon X300 Series express video card or above
NVIDIA GeForce 7 Series express video card or above

