

ATA COMMAND TABLE (in Alphabetic Order)

ATA Command	Instruction			OP
ADD LAB(S) TO NV CACHE PINNED SET	AddPinSet			B6h
CFA ERASE SECTORS	CfaEraseSec	CFES		C0h
CFA FORMAT SECTORS	CfafmtTrk	CFFT		50h
CFA KEY MANAGEMENT CHANGE KEY MANAGEMENT VALUE	CfaKeyChange	CFKC		B9h
CFA KEY MANAGEMENT READ KEY MATERIAL	CfaRdKey	CFRK		B9h
CFA KEY MANAGEMENT STRUCTURE READ	CfaStdRead	CFSR		B9h
CFA REQUEST EXTENDED ERROR	CfaReqErr	CFRE		03h
CFA TRANSLATE SECTOR	CfaTransSec	CFTS		87h
CFA WEAR LEVEL	CfaWearLevel	CFWL		F5h
CFA WRITE MULTIPLE WITHOUT ERASE	CfaWrMul	CFWM		CDh
CFA WRITE SECTOR(S) WITHOUT ERASE	CfaWrSec	CFWS		38h
CFA WRITE VERIFY	CfaWrVerify	CFWV		3Ch
CHECK MEDIA CARD TYPE	ChkMedType	CHMT		D1h
CHECK POWER MODE	ChkPwrMode	CKPW	CHPW	E5h
CONFIGURE STREAM	CfgStr	CFST		51h
DEVICE CONFIGURATION FREEZE LOCK	DevCfgFrzLock	DCOF	DCFL	B1h
DEVICE CONFIGURATION IDENTIFY	DevCgflDfy	DCOI	DCFI	B1h
DEVICE CONFIGURATION RESTORE	DevCfgRestore	DCOR	DEFR	B1h
DEVICE CONFIGURATION SET	DevCfgSet	DCOS	DCFS	B1h
DEVICE RESET	DevRst	DRST		08h
DOWNLOAD MICROCODE	Download	DNLD		92h
EXECUTE DEVICE DIAGNOSTIC	Diagnose	DIAG		90h
FLUSH CACHE	FlushCache	FLSH		E7h
FLUSH CACHE EXT	FlushCacheEx	FLSE	FLEX	EAh
FLUSH NV CACHE	FlushNV			B6h
GET MEDIA STATUS	GetMedStatus	GTMS		DAh
IDENTIFY DEVICE	Identify	IDFY		ECh
IDENTIFY PACKET DEVICE	IdfyPktDev	IDPD		A1h
IDLE		IDLE		E3h
IDLE IMMEDIATE	IdleIm	IDLI		E1h
INITIALIZE DEVICE PARAMETERS	InitDevPara	SETP		91h
MEDIA EJECT	MedEject	EJCT		EDh
MEDIA LOCK	MedLock	LOCK		DEh
MEDIA UNLOCK	MedUnlock	UNLK		DFh
NOP		NOP		00h
QUERY NV CACHE MISSES	QueryMiss			B6h
QUERY NV CACHE PINNED SET	QueryPinSet			B6h
READ BUFFER	RdBuf	RBUF		E4h

READ DMA	RdDma	RDMA		C8h
READ DMA EXT	RdDmaEx	RDMX		25h
READ DMA QUEUED	RdDmaQ	RDMQ		C7h
READ DMA QUEUED EXT	RdDmaQEx	RDOX		26h
READ DMA WITHOUT RETRIES	RdDMAN	RDMAN		C9h
READ FPDMA QUEUED	RFPDMAQ	RDMA_NCO		60h
READ LOG DMA EXT	RdLogEx_DMA	RLEX_DMA		47h
READ LOG EXT	RdLogEx	RLEX		2Fh
READ LOG EXT COMPREHENSIVE	RdLogExComp	RLEC		2Fh
READ LOG EXT DIR	RdLogExDir	RLED		2Fh
READ LOG EXT SELF TEST	RdLogExSelfTest	RLET		2Fh
READ LONG	RdLong	RDLG		22h
READ LONG WITHOUT RETRIES	RdLongN	RLN	RDLGN	23h
READ MULTIPLE	RdMul	RMUL		C4h
READ MULTIPLE EXT	RdMulEx	RDME	RMEX	29h
READ NATIVE MAX ADDRESS	RdNativeMax	RNMA		F8h
READ NATIVE MAX ADDRESS EXT	RdNativeMaxEx	RNME		27h
READ SECTOR(S)	RdSec	RDSK	RSEC	20h
READ SECTOR(S) EXT	RdSecEx	RDSE	RSEX	24h
READ SECTOR(S) WITHOUT RETRIES	RdSecN	RDSKN RSECN	RSN	21h
READ STREAM DMA EXT	RdStrDma	RSTD		2Ah
READ STREAM ERROR LOG	RdStrErrLog	RSTE		2Fh
READ STREAM EXT	RdStrPio	RSTP		2Bh
READ STREAM PERFORMANCE LOG	RdStrPfmLog	RPFM		2Fh
READ VERIFY SECTOR(S)	RdVfy	RVFY		40h
READ VERIFY SECTOR(S) EXT	RdVfyEx	RVFE		42h
READ VERIFY SECTOR(S) WITHOUT RETRIES	RdVfyN	RVFN	RVN	41h
REMOVE LAB(S) FROM NV CACHE PINNED SET	RmvPinSet			B6h
RETURN NV CACHE POWER MODE	RtnPwrMode			B6h
SCT LBA SEGMENT ACCESS	SCT_LSAP SCT_LSAP_GPL	SCT_LSA SCT_LSAP		
SCT READ LONG	SCT_RL_GPL	SCT_RL		
SCT WRITE LONG	SCT_WL_GPL	SCT_WL		
SCT RETURN ERROR RECOVERY CONTROL	SCT_RERC_GPL	SCT_RERC		
SCT RETURN FEATURE CONTRLL	SCT_RFC_GPL	SCT_RFC		
SCT RETURN FEATURE OPTION FLAG	SCT_RFOF_GPL	SCT_RFOF		
SCT RETURN SCT DATA TABLE	SCT_DT_GPL	SCT_DT		
SCT SET ERROR RECOVERY CCONTROL	SCT_SERC_GPL	SCT_SERC		
SCT SET FEATURE CONTRLL	SCT_SFC_GPL	SCT_SFC		
SCT STATUS REQUEST	SCT_REQST_GPL	SCT_REQST		
SECURITY DISABLE PASSWORD	SecuDisPsw	SEDP		F6h
SECURITY ERASE PREPARE	SecuErasePrep	SERP		F3h
SECURITY ERASE UNIT	SecuEraseUnit	SEEU		F4h
SECURITY FREEZE LOCK	SecuFrzLock	SFZL		F5h
SECURITY SET PASSWORD	SecuSetPsw	SESP		F1h

SECURITY UNLOCK	SecuUnlock	SEUL		F2h
SEEK		SEEK		70h
SERVICE	Service	SRVC		A2h
SET FEATURES	SetFeature	SETF		EFh
SET MAX ADDRESS	SetMaxAddr	SMXA	SMAX	F9h
SET MAX ADDRESS EXT	SetMaxEx	SAME		37h
SET MAX FREEZE LOCK	SetMaxFrzLock	SMFL		F9h
SET MAX LOCK	SetMaxLock	SMLK		F9h
SET MAX SET PASSWORD	SetMaxSetPswd	SMSP		F9h
SET MAX UNLOCK	SetMaxUnlock	SMUN		F9h
SET MULTIPLE MODE	SetMul	SMUL		C6h
SET NV CACHE POWER MODE	SetPwrMode			B6h
SLEEP	Sleep	SLEP		E6h
SMART DISABLE OPERATIONS	SmDisable	SDSO	SMDI	B0h
SMART ENABLE OPERATION	SmEnable	SESO	SMEN	B0h
SMART ENABLE/DISABLE AUTO OFFLINE		SAOL		B0h
SMART ENABLE/DISABLE AUTOSAVE	SmAutoSv	SAAS	SMAS	B0h
SMART EXECUTE OFFLINE IMMEDIATE	ExeSmO	SEOI	SMOI	B0h
SMART READ ATTRIBUTE THRESHOLDS	SmRdAtbThd	SRAT		B0h
SMART READ DATA	SmRdData	SMRD		B0h
SMART READ LOG	SmRdLog	SRLS	SMRL	B0h
SMART READ LOG COMPREHENSIVE	SmRdLogComp	SMRC		B0h
SMART READ LOG DIRECTORY	SmRdLogDir	SMLD		B0h
SMART READ LOG SELF TEST LOG	SmRdLogSelfTest	SMRT		B0h
SMART READ LOG SUMMARY	SmRdLogSum	SMRS		B0h
SMART RETURN STATUS	SmStatus	SRSS		B0h
SMART SAVE ATTRIBUTE VALUES	SmSvAtb	SSAV		B0h
SMART WRITE LOG	SmWrLog	SWLS	SMWL	B0h
SOFTWARE RESET	Reset	REST	SRST	
STANDBY	Standby	STBY		E2h
STANDBY IMMEDIATE	StandbyIm	STBI		E0h
TRUSTED RECEIVE	TCG_Receive	TCG_RCV		5Ch
TRUSTED RECEIVE DMA	TCG_Receive_DMA	TCG_RCV_DMA		5Dh
TRUSTED SEND	TDG_Send			5Eh
TRUSTED SEND DMA	TDG_Send_DMA			5Fh
WRITE BUFFER	WrBuf	WBUF		E8h
WRITE DMA	WrDma	WDMA		CAh
WRITE DMA EXT	WrDmaEx	WDMX		35h
WRITE DMA FUA EXT	WrDmaFuaEx	WDFE		3Dh
WRITE DMA QUEUED	WrDmaQ	WDMQ		CCh
WRITE DMA QUEUED EXT	WrDmaQEx	WDOX		36h
WRITE DMA QUEUE FUA EXT	WrDmaQFuaEx	WDOF		3Eh
WRITE DMA WITHOUT RETRIES	WrDmaN	WDMAN		CBh
WRITE FPDMA QUEUED	WFPDMAQ	WDMA_NCQ		61h
WRITE LOG DMA EXT	WrLogEx_DMA	WRLE_DMA		57h

WRITE LOG EXT	WrLogEx	WRLE		3Fh
WRITE LONG	WrLong	WTLG		32h
WRITE LONG WITHOUT RETRIES	WrLongN	WTLGN	WLN	33h
WRITE MULTIPLE	WrMul	WMUL		C5h
WRITE MULTIPLE EXT	WrMulEx	WDME	WMEX	39h
WRITE MULTIPLE FUA EXT	WrMulFuaEx	WMFE		CEh
WRITE SECTOR(S)	WrSec	WDSK	WSEC	30h
WRITE SECTOR(S) EXT	WrSecEx	WDSE	WSEX	34h
WRITE SECTOR(S) WITHOUT RETRIES	WrSecN	WDSKN WSECN	WSN	30h
WRITE STREAM DMA EXT	WrStrDma	WSTD		3Ah
WRITE STREAM ERROR LOG	WrStrErrLog	WSTE		2Fh
WRITE STREAM EXT	WrStrPio	WSTP		3Bh
WRITE UNCORRECTABLE EXT		WUNCX	WUNCX	45h
WRITE UNCORRECTABLE EXT_FL		WUNCX_ FL		45h
WRITE UNCORRECTABLE EXT_FNL		WUNCX_ FNL		45h
WRITE UNCORRECTABLE EXT_PL		WUNCX_ PL		45h
WRITE UNCORRECTABLE EXT_PNL		WUNCX_ PNL		45h
WRITE VERIFY	WrVerify	WV		3Ch